

## MX95/105 Datasheet

By Amon Stinson, Don Vo and Simarbir Singh



The network performance benchmarks listed in the KB are target numbers based on initial testing and can change on further testing.

---

## Overview

The Meraki **MX95/105** is an enterprise security appliance designed for distributed deployments that require remote administration across Medium branch environments. It is ideal for network administrators who demand both ease of deployment and a state-of-the-art feature set. The Meraki Dashboard allows for simple and easy deployment of the MX95/105 with minimal pre-configuration in almost any location.

Providing 4 x dedicated WAN uplinks, 2 x 10G SFP+ ports and 2 x RJ45 2.5G mGig ports. The LAN ports include 4 x RJ45 1GbE ports, and 2 x SFP+ 10G ports, the MX95/105 is ready for deployment in a variety of enterprise environments. MX95/105 appliance provides the following features:



---

## Features

- Managed via Cisco Meraki Dashboard
- Automatic Firmware upgrades
- Meraki AutoVPN and L2TP/IPSec VPN endpoint
- Active Directory integration

- WAN Link Balancing
- Automatic WAN Failover
- SD-WAN over Meraki AutoVPN
- L3/L7 Stateful Firewall
- Geo based firewall rules
- 1:1 and 1:Many NAT
- Configurable VLANs / DHCP support
- Static Routing
- Client VPN endpoint
- Content Filtering
- Malware Protection (AMP) w/ optional Threat Grid integration
- IDS/IPS protection
- Custom Traffic Shaping
- Historical Client Usage statistics
- Netflow support
- Syslog integration
- Remote Packet Capture tools

---

## Interfaces

- 2 x SFP+ / 10 Gigabit Ethernet ports dedicated for the WAN uplink
- 1 x RJ45 / 2.5 Gigabit Ethernet port dedicated for the WAN uplink
- 1 x RJ45 / 2.5 Gigabit Ethernet port with PoE+ capabilities dedicated for the WAN uplink
- 4 x RJ45 / 1 Gigabit Ethernet LAN ports
- 2 x SFP+ / 10 Gigabit Ethernet LAN ports
- 1 x RJ45 management port for local status page access
- 1 x USB 3.0 port

---

## Context and Comparisons

	<u><b>MX85</b></u>	<u><b>MX95</b></u>	<b>MX105</b>
<b># of WAN Uplinks</b>	4	4	4
<b>Stateful Firewall Throughput</b>	1 Gbps	2 Gbps	3 Gbps
<b>Maximum VPN Throughput</b>	500 Mbps	800 Mbps	1 Gbps
<b>Advanced Security Throughput</b>	750 Mbps	1Gbps	1.5 Gbps
<b>PoE Capabilities</b>	Yes, 1x RJ45 / 1 Gigabit Ethernet port (WAN)	Yes, 1x RJ45 / 1 Gigabit Ethernet port (WAN)	Yes, 1x RJ45 / 1 Gigabit Ethernet port (WAN)

---

---

## Technical Breakdown

### WAN Interface

#### MX85

2 x Dedicated 1 Gigabit Ethernet SFP  
2 x Dedicated 1 Gigabit Ethernet RJ45

#### MX95/105

2x Dedicated 10 Gigabit Ethernet SFP+  
2x Dedicated 2.5 Gigabit Ethernet RJ45



**Note:** The MX firmware currently supports a maximum of two Active WAN Uplinks. For more information about the interface behaviors, please refer to our [WAN behavior on MX75/85/95/105 documentation](#).

### LAN Interface

#### MX85

8 x Dedicated 1 Gigabit Ethernet RJ45  
2x Dedicated 1 Gigabit Ethernet SFP

#### MX95/105

4 x Dedicated 1 Gigabit Ethernet RJ45  
2 x Dedicated 10 Gigabit Ethernet SFP+

### Throughput and Capabilities

	<u>MX85</u>	<u>MX95</u>	<u>MX105</u>
<b>Recommended Use Case</b>	Small to medium branch with up to 250 users	Mid to large enterprise locations with 500 users	Mid to large enterprise locations with 750 users
<b>Max site-to-site VPN Throughput</b>	500 Mbps	800 Mbps	1 Gbps
<b>Max Concurrent site-to-site VPN Tunnels</b>	200	500	1000
<b>Max Stateful Firewall Throughput</b>	1 Gbps	2 Gbps	3 Gbps
<b>Max Throughput with All Advanced Security features</b>	750 Mbps	1Gbps	1.5 Gbps

### Physical

	<u>MX85</u>	<u>MX-95</u>	<u>MX105</u>
<b>Mount Type</b>	Rack Mount	Rack Mount	Rack Mount
<b>Dimensions</b>	1.7" x 9.8" x 19"	1.73" x 11.23" x 19"	1.73" x 12.4" x 19"

<b>(h x d x w)</b>	43.8 x 250 x 484.6mm	44 x 285.2 x 484.6mm	44 x 315 x 484.6mm
<b>Weight</b>	8.2lb (3.7kg)	6.99lbs (3.17kg)	10.74lbs
			(4.87kg)
			2 Fans and 2 PSUs inserted
<b>Input Operating Voltage</b>	90-264VAC	100-127VAC,	100-127VAC,
	(47-63Hz)	200-240VAC (50/60Hz)	200-240VAC (50/60Hz)
<b>PSU Model Number</b>	N/A	N/A	Removable
			MA-PWR-150W AC
<b>Power Load (idle/max)</b>	12W / 55W	42W/ 109W	53W/ 123W
<b>Operating Temperature</b>	32°F to 104°F	32°F to 104°F	32°F to 104°F
	(0°C to 40°C)	(0°C to 40°C)	(0°C to 40°C)
<b>Humidity</b>	5% to 95%	5% to 95%	5% to 95%

---

## Accessories

Accessory	Description
<b>MA-PWR-CORD-US</b>	1x AC Power Cable, US plug
<b>MA-PWR-CORD-EU</b>	1x AC Power Cable, EU plug
<b>MA-PWR-CORD-UK</b>	1x AC Power Cable, UK plug
<b>MA-PWR-CORD-AU</b>	1x AC Power Cable, AU plug
<b>MA-RCKMNT-KIT-1</b>	Optional: Rack mount screws kit. (Not included with MX95 and MX105)

## Compatible Fiber Transceiver Modules

The Cisco Meraki MX95 and MX105 supports pluggable optics for high-speed backbone connections between wiring closets or to aggregation switches. Cisco Meraki offers several standards-based Gigabit and 10 Gigabit pluggable modules. Each appliance has also been tested for compatibility with several third party modules.

Product ID	Fiber Type
<b>MA-SFP-1GB-SX</b>	Multi-Mode Fiber (MMF)
<b>MA-SFP-1GB-LX10</b>	Single-Mode Fiber (SMF)

---

<b>MA-SFP-1GB-TX</b>	N/A (RJ45 Copper SFP)
<b>MA-SFP-10GB-SR</b>	Multi-Mode Fiber (MMF)
<b>MA-SFP-10GB-LR</b>	Single-Mode Fiber (SMF)
<b>MA-SFP-10GB-LRM</b>	Single-Mode Fiber (SMF)
<b>MA-SFP-10GB-LRM</b>	Multi-Mode Fiber (MMF)
<b>MA-SFP-10GB-ER2</b>	Single-Mode Fiber (SMF)
<b>MA-SFP-10GB-ZR</b>	Single-Mode Fiber (SMF)

### Direct Attach

<b>Product ID</b>	<b>Description</b>
<b>MA-CBL-TA-1M</b>	10GSFP+Cu, 1m Passive Twinax
<b>MA-CBL-TA-3M</b>	10GSFP+Cu, 3m Passive Twinax



**Note:** Please refer to the [Meraki SFP Datasheet](#) for additional information about the SFP Accessories

## Troubleshooting

### Common Event Log Messages

There are currently no MX95/105 specific event log entries, for more general information about navigating the event log and the types of events that could be expected, please check out our [Event Log documentation](#).